

## PM2018A

600A AC CLAMP METER



- 6,000 counts LCD display with backlit
- **LPF** (low-pass filter) of 1kHz, 3dB.
- Data hold for easy reading
- Auto power off
- Low battery indication
- Safety as per IEC1010-1 CAT.III 600V

### Technical specifications

DCV: 600V,  $\pm 0.5\%$

ACV(40~65Hz): 600V,  $\pm 0.8\%$

ACA(40~65Hz): 6/60/600A,  $\pm 2.5\%$

OHM: 6k/60k $\Omega$ ,  $\pm 0.8\%$

Audible continuity: <30 $\Omega$

Clamp size:  $\Phi 24\text{mm}$  (max.)

Battery: 1.5Vx2, AAA size

Dimensions: 187x65x38mm, 250g approx.

Accessories: carrying bag

**PEAKMETER**<sup>®</sup>

by Sinometer

[www.peak-meter.cn](http://www.peak-meter.cn)

Email: [sales@peak-meter.cn](mailto:sales@peak-meter.cn)